



ZEISS CALYPSO

# Zeiss PDF Printer Manual Setup



Greg Ellington  
Applications Engineer  
Carl Zeiss Industrial Metrology, LLC  
9/22/2016

# Setting up the Zeiss PDF Printer and Zeiss PDF Printer7

For Zeiss PDF printing to function properly, it is necessary for the printers to exist as a printer in Control Panel. This is seen under **Control Panel -> Devices and Printers**.




Figure 1. Control Panel -> Devices and Printers

Observe in Figure 1 that Zeiss PDF Printer and Zeiss PDF Printer7 are both missing, which means that CALYPSO PDF printing is currently disabled. To set this up, if not on the list, the printer(s) will need to be installed. Normally, this step is completed by the Zeiss PDF Printer installation of the CALYPSO installation. To determine what has been installed, look within **Control Panel -> Programs and Features** (figure 2) for **both** Zeiss PDF Printer and Zeiss PDF Printer7. These two printers are required. If both printers are not shown as installed, it is necessary to manually install the printer from the CALYPSO installation resources on either the DVD, [DVD Drive]:\CALYPSO\ISSetupPrerequisites\{02C1DFCB-65DF-4452-A49D-3D17B46D3F16}\ZeissPdfInstall.vbe or within the installation folder, C:\Program Files (x86)\Zeiss\CALYPSO 6.2\tools\ZeissPdfInstall.vbe

The installation will walk you through the process. If both of the Zeiss PDF printers do not appear under **Control Panel -> Devices and Printers** as seen in figure 12, continue with the steps outlined in this document.




Figure 2. Control Panel -> Programs and Features

## Steps to Install Zeiss PDF Printer(s) manually

1. Decide which printer to install (first), Zeiss PDF Printer or Zeiss PDF Printer7.
2. Click **Add a printer** (figure 1)
3. Click **Add a local printer** (figure 3)




Figure 3. Add a local printer

4. Choose a printer port.

For Zeiss PDF Printer, select **NV05: (novaPDF Pro Server Port)**

For Zeiss PDF Printer7, select **NVK7: (NovaPDF Port)**




Figure 4: Add Printer->choose printer port

5. Select the **Generic / Text Only** driver. This will use the proper printer icon for the printer list.




Figure 5: Add Printer->install printer driver

6. If prompted, select "Use the driver that is currently installed (recommended)".




Figure 6. Add Printer->select driver version

7. Enter the name of the printer. "Zeiss PDF Printer" (or "Zeiss PDF Printer7" – **note there is no space between Printer and 7**).




Figure 7. Add Printer->printer name

8. Do not share the printer.




Figure 8. Add Printer->printer sharing

9. Click **Finish** to complete the installation. You may “Set as the default printer”, if you desire.




Figure 9. Add Printer - Finish

## Setup Printer Properties

10. In **Control Panel -> Devices and Printers**, right-click the printer added and choose **Printer properties**.




Figure 10. Control Panel -> Devices and Printers, Printer properties

11. Go to the **Advanced** tab of **Zeiss PDF Printer Properties**, and select the correct Driver.




Figure 11. Zeiss PDF Printer Properties, Advanced tab

Zeiss PDF Printer: **novaPDF Pro Server 5 Printer Driver**

Zeiss PDF Printer7: **novaPDF 7 Printer Driver**

12. Uncheck **Print spooled documents first**, and click **OK**.

These steps must be done for Zeiss PDF Printer and Zeiss PDF Printer7, if they are missing from the printer list. Therefore, repeat these steps for the other missing printer, if necessary.




Figure 12. Control Panel -> Devices and Printers, both Zeiss PDF Printers are installed